

innovative **PORTABLE** audio



# FENDER® PASSPORT® DELUXE PD-250 PLUS

## Portable Sound System

The PD-250 PLUS is the flagship model of the Passport product line and includes a built-in CD-player. The PD-250 PLUS features a six channel mixer, 250-Watt stereo amp and a specialized DSA speaker design – the PD-250 PLUS provides powerful and full sound in a portable and easy to use design. If it's a coffee shop performance, aerobics class or corporate event, the PD-250 PLUS is great in any situation where quality sound is needed.

### The Passport PD-250 PLUS is perfect for use in:

- Groups up to 300-500 people in size
- Corporate presentations
- Health and fitness classes
- Mobile DJ's
- Schools
- Sporting events

### The Passport PD-250 PLUS has the following features:

- Black luggage-style molded case that protects the product during transportation from physical damage and the elements
- Built-in CD-Player
- Six-channel mixer: four mic/line, one stereo, one CD-player
- 250 Watts (125 per channel) stereo Class-D technology
- Digital reverb
- Proprietary DSA speaker design featuring two 5.5" woofer and dual arrayed 2.75" tweeters per speaker enclosure
- Two P-51 microphone (with mic clips, cables and carry pouches)
- Two 20" speaker cables
- Compatible with Passport wireless accessories
- 53 lbs.

<b>Model Name</b>	Passport Deluxe PD-250 PLUS	
<b>Model Number</b>	069-3001-000 120V USA 069-3001-900 120V DS 069-3001-930 240V AUS	069-3001-940 230V UK 069-3001-960 230V EUR 069-3001-970 100V JPN
<b>Description</b>	Complete Self-Contained Portable Sound System With Built-In CD-Player	
<b>Series</b>	Passport systems	
<b>Dimensions</b>	Height: 24.2" (615 mm) Width: 33.7" (840 mm) Depth: 11.8" (300 mm)	
<b>Weight</b>	53 lbs. (24 kg)	
<b>Covering</b>	Black luggage-style molded case	
<b>Power Output</b>	250 Watts Stereo Class-D, (2 x 125 Watts) 8 Ohms per speaker cabinet	
<b>Input Power</b>	N/A	
<b>Features</b>	<ul style="list-style-type: none"> <li>• Built-In CD-Player</li> <li>• Docking Connector for Passport Wireless Receiver</li> <li>• Six Channel Mixer (4 Mic/Line, 1 Stereo, 1 CD-Player)</li> <li>• Microphone Channels 1-4 Controls; Level, Low, High, Rev/Aux, Pan</li> <li>• Stereo Channel 5 Controls; Level, Low, High, Rev/Aux, Balance</li> <li>• CD-Player Controls; Level, Low, High, Rev/Aux, Balance, Eject, Play/Pause, Stop, Mode, Previous Track/Rewind, Next Track/Fast Forward</li> <li>• Master Reverb Control</li> <li>• System EQ Control</li> <li>• Stereo RCA Out (Record Out)</li> <li>• Digital Reverb</li> <li>• 35 mm (1 3/8") Speaker Stand Adaptors are built into speaker cabinets</li> <li>• Two P-51 Mic Kits featuring: Professional Cardioid Low Impedance Dynamic Microphone 18' Microphone Cable, Mic Clip, Carry Pouch</li> <li>• Two 9 meter (27 feet) Speaker Cables</li> <li>• Detachable IEC power Cable</li> <li>• Switchable voltage power supply</li> </ul>	
<b>Introduced</b>	June 2007	
<b>Notice</b>	Product prices, Features and Specifications are subject to change without notice	

The Passport PD-250 PLUS will not operate with the Passport DC accessories.

For more information and to find a dealer near you, visit [www.fender.com/passport/](http://www.fender.com/passport/).

