

## An Overdrive Pedal that Reacts to You

The DN-2 is an exciting new type of overdrive pedal that reacts to the intensity of your performance. This unique BOSS pedal comes equipped with the acclaimed Dyna Amp technology recently introduced in Roland's popular CUBE-60 amp, letting you create unique tone transitions based on picking dynamics. It's possible to get a transparent clean output sound by playing softly, or a powerful heavy overdrive sound by picking aggressively.



- Provides dynamic transition between clean to heavy overdrive based on picking strength and/or guitar volume
- Acclaimed Dyna Amp technology derived from Roland's CUBE-60
- A unique way for guitarists to add expression to their performance
- Road-tough BOSS metal construction

\*Actual product appearance may be subject to change.

## **DN-2 Specifications**

■ Nominal Input Leve -20 dBu ■ Input Impedance 1 MΩ ■ Nominal Output Level -20 dBu ■ Output Impedance 1 kΩ ■ Recommended Load Impedance 10 kΩ or greater ■ Controls Pedal Switch, LEVEL Knob, TONE Knob, DRVE Knob ■ Indicator CHECK Indicator (Serves also as battery check indicator) ■ Connectors INPUT Jack, OUTPUT Jack, AC adaptor Jack ■ Power Supply DC 9 V: Dry battery 6F22 (9 V) type (carbon), Dry battery 6LR61 (9 V) type (alkaline), AC Adaptor (PSA series: optional) ■ Current Draw 36 mA (DC 9 V) ■ Expected battery life under continuous use Carbon: 3 hours, Alkaline: 10 hours ■ Dimensions 73 (W) x 129 (D) x 99 (H) mm, 2-7/8 (W) x 5-1/8 (D) x 2-3/8 (H) inches ■ Weight 440 g/1 lb

(including battery) ■ Accessories Owner's Manual, Leaflets (USING THE UNIT SAFELY, IMPORTANT NOTES, and Information), Dry Battery 006P/9V (6LR61) ■ Options AC Adaptor (PSA series)

\*The battery that was supplied with the unit is for temporary use - intended primarily for testing its operation.

\* We recommend that alkaline battery be used when replacing the battery.

\* 0 dBu= 0.775 Vrms

\* The specifications are subject to change without notice.